iGuzzini


Last information update: April 2025

Product configuration: RC54

RC54: Palco LV spotlight Ø 62 - Wide Flood beam - Bluetooth



144



RC54: Palco LV spotlight Ø 62 - Wide Flood beam - Bluetooth

Adjustable spotlight with adapter for installation on 48V low voltage track. Made of die-cast aluminium with passive dissipation system. The adapter made of a thermoplastic material includes the DC/DC driver circuit and Bluetooth protocol. The swivel joints allow the spotlight to be rotated by 360° and tilted by 90°. The set back position of the optic unit guarantees a high level of visual comfort. Superpure aluminium reflector with high definition OPTI BEAM technology. A rapid tool-free system for connecting the adapter electrically and mechanically to the track. The 48V track coupling device is fitted with a mechanical anti-fall safety double block. Luminaire with Bluetooth Low Energy technology (WiSilica). Frequency 2.4 GHz BLE. The luminaire can be controlled with the Quick BLE system and Smart Light Control app that enable on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via Smart Light Control (Eddystone, iBeacon, Alt Beacon) that enables functions including push notification and indoor navigation-wayfinding.

Installation

Colour

An adapter is used to fix the device mechanically and tool-free to the 48V track. Max luminaire-luminaire distance (*): 8 m; max smartphone-luminaire distance (*): 20 m.

Weight (Kg)

0.41

Ļω			
1			
		201	
	1	ā.	
_			

White (01) | Black (04)

Mounting Low voltage track

Wiring

Direct connection on 48V track. Track power supply unit to be ordered separately. Luminaire can be controlled with Bluetooth technology (WiSilica)

Notes

(*) The maximum distance for Bluetooth installations is affected by physical obstacles, like walls, metal panels and the layout of the system. We suggest that a test is conducted at the installation site. Technical and anti-glare accessories available; with option of the combined installation of two internal accessories.



Complies with EN60598-1 and pertinent regulations

Im source:2050Voltage [Vin]:48W source:18Lamp code:LEDLuminous efficiency (Im/W, real value):82.2Number of lamps for optical assembly:1Im in emergency mode:-ZVEI Code:LEDTotal light flux at or above an angle of 90° [Lm]:-ZVEI Code:LEDLight Output Ratio (L.O.R.)79LED current [mA]:520[%]:Power factor:See installation instructionsBeam angle [°]:42°Minimum dimming %:1CRI (minimum):90Control:Bluetooth WiSilica	Technical data			
Im source: 2050 Voltage [Vin]: 48 W source: 18 Luminous efficiency (Im/W, 82.2 Number of lamps for optical 1 real value): ZVEI Code: LED Im in emergency mode: ZVEI Code: LED Total light flux at or above 0 an angle of 90° [Lm]: ZVEI Code: LED Iumber of optical 1 Ausmber of optical 1 Ausmber of optical 2 LED current [mA]: 520 Power factor: See installation instructions Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	Im system:	1620	MacAdam Step:	2
W source: 18 Lamp code: LED Luminous efficiency (Im/W, 82.2 Number of lamps for optical 1 assembly: 1 real value): - ZVEI Code: LED Im in emergency mode: - ZVEI Code: LED Total light flux at or above 0 an angle of 90° [Lm]: Number of optical assemblies: 1 Light Output Ratio (L.O.R.) 79 LED current [mA]: 520 [%]: Power factor: See installation instructions Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	W system:	19.7	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25°C)
Luminous efficiency (Im/W, 82.2 Number of lamps for optical 1 assembly: Im in emergency mode: - Total light flux at or above 0 an angle of 90° [Lm]: ZVEI Code: LED Light Output Ratio (L.O.R.) 79 Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	Im source:	2050	Voltage [Vin]:	48
real value): assembly: Im in emergency mode: - Total light flux at or above 0 an angle of 90° [Lm]: Number of optical assemblies: Light Output Ratio (L.O.R.) 79 [%]: EED current [mA]: 520 Power factor: See installation instructions Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	W source:	18	Lamp code:	LED
Total light flux at or above 0 Number of optical assemblies: 1 an angle of 90° [Lm]: assemblies: 520 Light Output Ratio (L.O.R.) 79 LED current [mA]: 520 [%]: Power factor: See installation instructions Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica		82.2		1
an angle of 90° [Lm]: assemblies: Light Output Ratio (L.O.R.) 79 [%]: LED current [mA]: 520 Power factor: See installation instructions Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	Im in emergency mode:	-	ZVEI Code:	LED
[%]: Power factor: See installation instructions Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	0	0		1
Beam angle [°]: 42° Minimum dimming %: 1 CRI (minimum): 90 Control: Bluetooth WiSilica	Light Output Ratio (L.O.R.)	79	LED current [mA]:	520
CRI (minimum): 90 Control: Bluetooth WiSilica	[%]:		Power factor:	See installation instructions
	Beam angle [°]:	42°	Minimum dimming %:	1
	CRI (minimum):	90	Control:	Bluetooth WiSilica
Colour temperature [K]: 2700	Colour temperature [K]:	2700		

