Design iGuzzini

iGuzzini

Last information update: March 2025

Product configuration: S682+X801.01+X806.01

S682: Wall-mounted luminaire - Warm White - Integrated power supply - AS (Up) optic

X801.01: Flush-mounted polycarbonate guard - for Allure 120x250 - White

X806.01: Spacer base for installation via conduit - for Allure 120x250 - White



253

96

Product code

S682: Wall-mounted luminaire - Warm White - Integrated power supply - AS (Up) optic

Technical description

Wall-mounted luminaire with Warm White LED lamps, AS (Up) optic Consists of an optical assembly, a top glass, a bottom glass and a cover guard to be purchased separately. The optical assembly is made of an aluminium alloy, subjected to a multi-step, pretreatment process in which the main phases are degreasing, fluorozirconation (a protective surface film) and sealing (with a nanostructured silane layer). The following painting stage consists of a primer and a liquid acrylic paint, cured at 150°C, with a high level of weather and UV ray resistance. The tempered sodium-calcium upper cover glass has black serigraphy on the edge and is 5mm thick. The tempered sodium-calcium lower cover glass has black serigraphy on the edge and is 4mm thick. The product is supplied with an aluminium optic in a set back position for the lower optical assembly to obtain maximum visual comfort and a flush-mounted aluminium optic for the upper optical assembly to obtain maximum efficiency. Fitted with 2 PG13.5 cable gland for 8.5mm to 12.5mm diameter cables. All external screws used are made of A2 stainless steel.

The product is fixed to the wall by opening the plate on the back of it, securing it to the wall and then rapidly fixing the luminaire to it.

Weight (Kg) White (01) | Black (04) | Green (07) | Grey (15) | Rust Brown (F5) 2.49



wall arm

Notes

The guard (whether flush-mounted, with a visible border or a PMMA screen) must be fitted and can be purchased separately.

Complies with EN60598-1 and pertinent regulations



IK06

















Accessory code

X801.01: Flush-mounted polycarbonate guard - for Allure 120x250 - White

Polycarbonate guard to be installed in the lower part of the Allure product. The guard is flush-mounted using two stainless steel screws. Coated with two-component liquid paint (catalyst+ enamel).

Installation

The product is installed using two stainless steel screws.

Colour Weight (Kg) White (01) 0.04

Complies with EN60598-1 and pertinent regulations



Accessory code


X806.01: Spacer base for installation via conduit - for Allure 120x250 - White

Technical description

Die-cast aluminium spacer base designed for installing the Allure product via conduit tubes. The base is fitted with 2 holes (one on each side and two on the upper side of the accessory). The accessory code includes 4 rubber stoppers for the holes that are not used during installation.

Colour Weight (Kg) White (01)

Complies with EN60598-1 and pertinent regulations



| Life Time LED 2: 100,000h - L80 - B10 (Ta 40°C) N system: 10.5 Lamp code: LED Number of lamps for optical assembly: Luminous efficiency (lm/W, 109.4 eal value): Vumber of optical assembles: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) 71 Power factor: See installation instructions inrush current: 5 A / 50 µs Maximum number of luminaires of this type per miniature circuit breaker: B16A: 50 luminaires | | | | |
|--|--|--------------------------------|-----------------------------|--------------------------------|
| N system: 10.5 m source: 1630 N source: 8.5 Luminous efficiency (lm/W, 109.4 eal value): 2VEI Code: LED Number of optical assembly: 2VEI Code: LED Number of optical assembly: 2VEI Code: LED Number of optical assemblis: 1149 assemblise: Intervallo temperatura ambiente: 1149 and angle of 90° [Lm]: 149 angle of 90° [Lm]: | Technical data | | | |
| M source: | Im system: | 1149 | Life Time LED 2: | 100,000h - L80 - B10 (Ta 40°C) |
| Assembly: Luminous efficiency (lm/W, 109.4 assembly: Luminous efficiency (lm/W, 109.4 assembly: ZVEI Code: LED Number of optical 1 assemblies: Intervallo temperatura ambiente: Light Output Ratio (L.O.R.) 71 Power factor: See installation instructions inrush current: 5 A / 50 µs Maximum number of luminaires of this type per miniature circuit breaker: MacAdam Step: 3 LED Number of optical 1 assemblies: From -30°C to 50°C. Ambiente: Power factor: See installation instructions inrush current: 5 A / 50 µs Maximum number of luminaires of this type per miniature circuit breaker: B10A: 31 luminaires B16A: 50 luminaires B16A: 50 luminaires C16A: 85 luminaires Minimum dimming %: 1 Overvoltage protection: 4kV Common mode & 2kV Differential mode | W system: | 10.5 | Lamp code: | LED |
| Luminous efficiency (Im/W, eal value): m in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Total (Iminimum): Bo Colour temperature [K]: MacAdam Step: Jife Time LED 1: See installation instructions MacAdam Step: Jintervallo temperatura Ambiente: Power factor: Bo Maximum number of John Step Step Step Step Step Step Step Step | Im source: | 1630 | Number of lamps for optical | 1 |
| eal value): m in emergency mode: Fotal light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Folial light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Folial light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Folial light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Folial light flux at or above an above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Folial light flux at or above an above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Folial light flux at or above an assemblies: Intervallo temperatura ambiente: Fower factor: Folial light flux at or above an assemblies: Intervallo temperatura ambiente: See installation instructions Inrush current: Folial light flux at or above an assemblies: Intervallo temperatura ambiente: See installation instructions Inrush current: Folial light flux at or above ambiente: Intervallo temperatura ambiente: See installation instructions Inrush current: Folial light flux at or above ambiente: Intervallo temperatura ambiente: See installation instructions Inrush current: Folial light flux at or above ambiente: Intervallo temperatura ambiente: See installation instructions Inrush current: Folial light flux at or above ambiente: Intervallo temperatura ambiente: See installation instructions Inrush current: Folial light flux at or above ambiente: Intervallo temperatura amb | W source: | 8.5 | assembly: | |
| m in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Total light flux at or above an above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) Total light flux at or above an above ambiente: Power factor: See installation instructions inrush current: 5 A / 50 μs Maximum number of luminaires of this type per miniature circuit breaker: MacAdam Step: 3 100,000h - L80 - B10 (Ta 25°C) Minimum dimming %: Overvoltage protection: 4kV Common mode & 2kV Differential mode | Luminous efficiency (lm/W, | 109.4 | ZVEI Code: | LED |
| Fotal light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) 71 Power factor: See installation instructions Inrush current: 5 A / 50 μs RI (minimum): 80 Maximum number of luminaires of this type per miniature circuit breaker: B16A: 50 luminaires Life Time LED 1: 100,000h - L80 - B10 (Ta 25°C) Minimum dimming %: 1 Overvoltage protection: 4kV Common mode & 2kV Differential mode | real value): | | • | 1 |
| an angle of 90° [Lm]: ambiente: Power factor: See installation instructions Inrush current: 5 A / 50 μs Maximum number of Iuminaires of this type per MacAdam Step: 3 Inrush current: 100,000h - L80 - B10 (Ta 25°C) Minimum dimming %: 100,000h - L80 - B10 (Ta 25°C) | Im in emergency mode: | - | assemblies: | |
| %]: CRI (minimum): 80 Colour temperature [K]: Maximum number of luminaires of this type per miniature circuit breaker: 3 100,000h - L80 - B10 (Ta 25°C) Minimum dimming %: Overvoltage protection: S A / 50 μs Maximum number of luminaires B10A: 31 luminaires B16A: 50 luminaires C10A: 52 luminaires C16A: 85 luminaires 4kV Common mode & 2kV Differential mode | Total light flux at or above an angle of 90° [Lm]: | 1149 | | from -30°C to 50°C. |
| CRI (minimum): 80 Colour temperature [K]: 2700 MacAdam Step: 3 Life Time LED 1: 100,000h - L80 - B10 (Ta 25°C) Minimum dimming %: 1 Overvoltage protection: 4kV Common mode & 2kV Differential mode | Light Output Ratio (L.O.R.) [%]: | 71 | Power factor: | See installation instructions |
| Colour temperature [K]: 2700 MacAdam Step: 3 100,000h - L80 - B10 (Ta 25°C) Minimum dimming %: 1 Overvoltage protection: B10A: 31 luminaires B16A: 50 luminaires C10A: 52 luminaires C16A: 85 luminaires C | | | Inrush current: | 5 A / 50 μs |
| MacAdam Step: 3 miniature circuit breaker: B16A: 50 luminaires C10A: 52 luminaires C16A: 85 luminaires C16A: 85 luminaires Minimum dimming %: 1 Overvoltage protection: 4kV Common mode & 2kV Differential mode | CRI (minimum): | 80 | Maximum number of | |
| Life Time LED 1: 100,000h - L80 - B10 (Ta 25°C) C10A: 52 luminaires C16A: 85 luminaires Minimum dimming %: 1 Overvoltage protection: 4kV Common mode & 2kV Differential mode | Colour temperature [K]: | 2700 | | B16A: 50 luminaires |
| Minimum dimming %: 1 Overvoltage protection: 4kV Common mode & 2kV Differential mode | MacAdam Step: | 3 | | |
| Overvoltage protection: 4kV Common mode & 2kV Differential mode | Life Time LED 1: | 100,000h - L80 - B10 (Ta 25°C) | | |
| Differential mode | | | Minimum dimming %: | 1 |
| Control: DALI-2 | | | Overvoltage protection: | |
| | | | Control: | DALI-2 |

Polar

