


Quick DALI

Design iGuzzini

iGuzzini

Last information update: February 2023



Product code

9718: LMS Quick DALI **Attention! Code no longer in production**

Technical description

Control panel that can be used as a DALI system open to 64 addresses, in connection with the SW and programming interface item code 9721. It can be configured using a PC and can retrieve up to a maximum of 7 groups or 7 scenes (the +, – and On/Off keys remain unchanged). Using the Plug&Play device item code 9723, the control panel can directly control 4 DALI lines without requiring any programming. Function: general adjustment of ambient lights via the + and – keys. Separate adjustment of A, B, C and D lamp groups (with item code 9723). Retrieves up to 3 scenes. Entire environment switched on/off via On/Off key. If there is at least one multi-sensor, scene 3 retrieves the automatic adjustment mode for artificial light according to the amount of daylight (energy saving). RGB luminaires are controlled only on the D unit DALI output and only with certain types of iGuzzini luminaires. The panel has an IR receiver on the front to interact with a PC or remote control item code 9720). It cannot control luminaires with DT8 commands.

Installation

Mounted on a recessed box with a centre-to-centre distance of 60 mm or a 503 type 3-location box. Box item code ML15 available as an accessory.

Colour

Grey (15) | White (01)

Wiring

It must be powered using power feeder item code 9908 (available as an accessory)

Complies with EN60598-1 and pertinent regulations

