

---

## Constant current power supply unit DALI IP20 35W - VIN = 110-240VAC 50/60Hz Ø17

Design iGuzzini

iGuzzini

Last information update: February 2023



### Accessory code

PA72: Constant current power supply unit DALI IP20 35W - VIN = 110-240VAC 50/60Hz Ø17

---

### Technical description

DALI dimmable electronic ballast - 500 mA constant current operation. Protection devices: thermal, mains overvoltage, for overloads.

---

### Installation

remote installation - option of fastening to surfaces with screws

---

### Colour

Indeterminate (00)

---

### Dimension (mm) (\*)

124x79x22

\* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

---

### Wiring

500 mA for Ø17 Laser recessed luminaires - min 2 - max 20 used. Cables secured with screw terminals.

Complies with EN60598-1 and pertinent regulations

