Light Shed 60

Design iGuzzini

iGuzzini

Last information update: May 2024



Accessory code

PD11: Cover with bracket for external/semi-recessed camera - For Light Shed 60 | dB 60

Technical description

Circular cover complete with bracket for mechanically fastening an AXIS compatible camera

The camera remains in an external/semi-recessed position in relation to the cover.

The bracket is equipped with threaded holes that allow an AXIS compatible camera to be fitted directly to it.

Contact iGuzzini or check the instruction sheet to view the compatible models.

Installation

Installation on a non-luminous Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$. The height of the Light Shed $60 \mid dB 60 \mod e (codes PC81 PC83 RC89 RC94)$.

Colour

White (01)

Wiring

For the wiring follow the camera instructions and the instruction sheet for the module with support. A base code PD15 is available for covering the outlet of the video/Ethernet cable from the ceiling.

Notes

Camera not included.

Complies with EN60598-1 and pertinent regulations

IP20